



Combi-18-Powerstick large

- 2 x Powerstick-6
 - 4 x Ventus-18
- Verstärker Empfehlung:
- Powersoft X4, 4 x 1.600 W/8 Ω, 4 x 3.000 W/4 Ω
 - Powersoft T604, 4 x 1.250 W/8 Ω, 4 x 1.500 W/4 Ω

Combi-18sp-Powerstick large

- 2 x Powerstick-6
- 2 x Ventus-18
- 2 x Ventus-18sp

Powerstick-6

Frequenzgang	70 Hz - 22 kHz (- 10 dB) 140 Hz - 20 kHz (+/- 3 dB)
Abstrahlverhalten	asymmetrisch 100° bis 50° x 55°
Belastbarkeit	500 W AES / 1.000 W program / 2.000 W peak at 4 Ω
Schalldruck	123 dB SPL AES / 126 dB SPL program / 129 dB SPL peak
Komponenten	LF: 4 x 6,5" Tiefmitteltöner HF: 1 x 1" Kompressionstreiber
Anschlüsse	2 x Neutrik NL4 Speakon IN/OUT (durchgeschliffen), Belegung: 1+/1-
Maße	985 (H) x 220 (B) x 338 mm (T)

Ventus-18/18sp

Untere Grenzfrequenz	28 Hz (- 10 dB) 34 Hz (- 3 dB)
Belastbarkeit	1.200 W AES / 2.400 W program / 4.800 W peak an 8 Ω
Schalldruck	130 dB SPL AES / 133 dB SPL program / 136 dB SPL peak
Komponenten	1 x 18" Tieftöner mit 4" Schwingspule
Anschlüsse	2 x Neutrik NL4 Speakon IN/OUT (loop through), configuration: 2+/2-
Maße	580 (h) x 580 (w) x 780 mm (d)
Endstufe	4.6 kW, dreikanalig
Verstärkerleistung CH1	2.600 W/ 8 Ω, 2.200 W/ 4 Ω
Verstärkerleistung CH2 & CH3	750 W/ 8 Ω, 1.000 W/ 4 Ω, 750 W/ 2 Ω

